

AMPLIFIER

BOB 540

► Device Type

Class-D amplifier

► Technical Data

Power (sin.) at 8 Ohm
Power (sin.) at 4 Ohm
Frequency Range
THD
Damping factor at 8 Ohm/ 1 kHz
Input Sensitivity
Input Connections
Output Connections

3x 120 W
3x 180 W
20 Hz - 35 kHz
20 Hz - 20 kHz 1 W at max. 0,02 %
250
26 dB
Phoenix 3-pole, RM: 3,8 mm
Phoenix 2-pole, RM: 5,08 mm

► Dimensions

Color
Width
Height
Depth
Weight

Black
230 mm
88 mm
280 mm
4 kg

BOB 540+

► Bob 540+ has the same performance data as the Bob 540, but is additionally equipped with a DSP (Digital Sound Processor). BEC Akustik presets are already installed on the DSP. Our Bob 540+ is AES and Dante compatible or Milan.



Amplifier Bob 540 – 714109108280

Amplifier Bob 540+ – 4262477790006